


- + HIGHER YIELD: REDUCTION OF ELECTRICAL RESISTANCE
- + REDUCED LOSSES DURING PARTIAL SHADING
- + HIGH CLASS APPEARANCE: EASY INTEGRATION IN BUILDINGS
- + APPLICATIONS: RESIDENTIAL
- + ECO: ESPEACIALLY ECONOMIC AND RELIABLE



# ECO LINE HALF CELL FULL BLACK M108 / 395 - 415 W

### MONOCRYSTALLINE MODULE FAMILY



Longlife tested



Selection of components



Cross-linking degree test



Power proofed



Performance surplus of 0 Wp to 6.49 Wp



free cells



Safety provided



Special packing to avoid micro cracks in the cells



German warrantor

## ECO LINE HALF CELL FULL BLACK M108 / 395 - 415 W

Monocrystalline module family	Module typ	Module type LX - XXXM/182-108+   XXX = Rated power Pmpp			
Electrical data at STC					
Rated power Pmpp [Wp]	395.00	400.00	405.00	410.00	415.00
Pmpp range to	401.49	406.49	411.49	416.49	421.49
Rated current Impp [A]	12.80	12.88	12.95	13.02	13.09
Rated voltage Vmpp [V]	30.89	31.09	31.30	31.51	31.72
Short-circuit current Isc [A]	13.52	13.60	13.67	13.75	13.82
Open-circuit voltage Uoc [V]	36.77	37.01	37.26	37.51	37.76
Efficiency at STC up to	20.54%	20.79%	21.05%	21.30%	21.56%
Efficiency at 200 W/m²	19.98%	20.24%	20.48%	20.73%	20.98%
Electrical data at NOCT					
Power at Pmpp [Wp]	293.25	296.96	300.67	304.38	308.10
Rated current Impp [A]	10.34	10.40	10.46	10.52	10.57
Rated voltage Vmpp [V]	28.36	28.54	28.74	28.94	29.14
Short-circuit current Isc [A]	10.92	10.99	11.05	11.11	11.17
Open-circuit voltage Uoc [V]	33.94	34.18	34.42	34.66	34.90

Specification as per STC (Standard test conditions): irradiance  $1000 \, \text{W/m}^2$  | module temperature  $25^{\circ}\text{C}$  | Air Mass = 1.5 NOCT (nominal operating cell temperature): irradiance  $800 \, \text{W/m}^2$  | wind speed  $1 \, \text{m/sec}$  | ambient temperature  $20^{\circ}\text{C}$  | cell operating temperature  $45 \, \text{+/-}2^{\circ}\text{C}$  | Air Mass = 1.5

#### Limiting values

Max. system voltage [V]	1000 V or 1500 V
Max. return current [I]	25 A
Operating Temperature	-40 to 85°C
Safety class	II
Max. tested pressure load [Pa] <sup>2</sup>	5400
Max. tested tensile load [Pa] <sup>2</sup>	2400

## Temperature coefficient

Temperature coefficient [V] $\mid$ [I] $\mid$ [P] $-0.285 \%/^{\circ}C \mid 0.000$	049 %/°C   -0.360 %/°C
--	------------------------

#### **Specifications**


Number of cells (matrix)	108 (6 x 18) I 182 x 91 mm
Module dimensions (LxWxH)³   Weight	1724 mm x 1134 mm x 35 mm   22 kg
Front-side glass	3.2 mm tempered highly transparent, anti-reflection solar glass
Frame	stable, anodised aluminium frame
Junction Box	At least IP67
Cable	symmetrical cable lengths > 1.1 m and 1.1 m, 4 mm² solar cable
Diodes	3 Schottky Diodes
Plug-in connection	MC4 or equivalent (IP67)
Hail test (max. hailstorm)	Ø 45 mm   impact velocity 23 m/s ≙ 83 km/h

The specifications and average values can vary slightly. Relevant is the corresponding data of the individual measurement. Specifications are subject to change without notice. Measurement tolerance depending on equipment: rated power +/- 3%, other values +/- 10%. All information given in this data sheet correspondes to DIN EN 50380. A potential light-induced degradation of the power after commissioning is not considered here.

- Further information in the installation manuals.

  1 The specific warranty conditions are given under www.luxor.solar/downloads.html.
- $2\ Horizontal\ mounted$   $3\ Tolerance\ L/W = +/-\ 3\ mm.\ H\ +/-2mm, the\ dimensions\ given\ in\ the\ order\ confirmation\ will\ be\ decisive$
- 4 Location and dimensions of holes on request

#### Back - / Front -/ Side view3




Drilled holes4

B: 16 x ventilation


C: 8 x mounting D: 2 x earthing

#### **Electrical characteristics**

#### UI-diagram e.g. LX-400M/182-108+



#### UP-diagram e.g. LX-400M/182-108+



200 W/m<sup>2</sup> 400 W/m<sup>2</sup> 600 W/m<sup>2</sup>

800 W/m<sup>2</sup>  $1000\,W/m^2$ 

Luxor, your specialised company









Guidelines: 93/68/EEC 2014/35/EU, (LVD)

The validity of the certificates/listings for a specific country has to be examined under: www.luxor.solar/downloads.html